

SEQUENCE OF OPERATION

1. General lighting (a1, a2) Partial On to 50% and controlled receptacles Auto On when occupancy detected.
2. Manual On/Off/Dim general lighting (a1, a2) and down lighting (b, c, d) with scene switch or touch screen.
3. Scene settings
 - General Lighting (a1, a2) 100%, (b) 0%, (c) 0%, (d) 0%
 - Projection (a1, a2) 0%, (b) 75%, (c) 50%, (d) 0%
 - Conferecing (a1, a2) 50%, (b) 50%, (c) 25%, (d) 50%
 - All Off (a1, a2) 0%, (b) 0%, (c) 0%, (d) 0%
4. Lighting in primary (a1) and secondary (a2) daylight zones will continuously dim based on daylight contribution to maintain a consistent task level.
5. Auto off all lighting and controlled receptacles within 20 minutes of vacancy.

Note: Diagram is typical for space type. Provide proper quantity and type of occupancy sensors, switches, room controllers, daylighting sensors, etc., per code requirement for each space.

