

SEQUENCE OF OPERATION

1. General lighting (a, a1, a2) Partial On to 50%. when occupancy detected.
2. Manual On/Off/Dim general lighting (a, a1, a2) and down lighting (b) with scene switches.
3. Scene settings

General Lighting	(a, a1, a2) 100%, (b) 0%
Projection	(a, a1, a2) 0%, (b) 75%
Conferencing	(a, a1, a2) 50%, (b) 50%
All Off	(a, a1, a2) 0%, (b) 0%
4. Lighting in primary (a1) and secondary (a2) daylight zones will continuously dim based on daylight contribution to maintain a consistent task level.
5. Auto off all lighting within 20 minutes of occupants leaving

Note: Diagram is typical for space type. Provide proper quantity and type of occupancy sensors, switches, room controllers, daylighting sensors, etc., per code requirement for each space.

